

ARDITO 3-1/2" & 4"

Performance 2 / ELV
Lumileds Luxeon COB 1205
ERP ESS030W-0550-42

CONTRASTE**DIMMING INFORMATIONS**

- Dimmers used: ELV only
- Audible noise: None
- Number of units tested: 1 to 10

Company	Models	Codes	Types	Dimming Performances		
				Programmable	Dimming Range *	Optimal Performance **
LUTRON	SKYLARK	SELV-300P	ELV	NA	8% - 100%	8% - 100%
	DIVA	DVELV-300P	ELV	NA	8% - 100%	10% - 100%
	RADIO RA2	RRD-6NA-WH	ELV	YES	3% - 100%	7% - 100%
	MAESTRO***	MAELV-600 Slider	ELV	NA	21% - 100%	12% - 100%
	GRAFIK T	GTJ-5NEM	ELV	YES	11% - 100%	11% - 100%
	SPACER SYSTEM	SPSELV-600	ELV	NA	13% - 100%	13% - 100%
	LEVITON	VIZIA	IPE04-1LZ	ELV	YES	24% - 100%
DECORA		6615-P	ELV	YES	13% - 100%	16% - 100%
VISIA RF +		VRE06-1LZ	ELV	YES	13% - 100%	25% - 100%
DECORA		DSE06-10Z	ELV	NA	6% - 100%	13% - 100%
DECORA		IPE04-LAW	ELV	YES	6% - 100%	16% - 100%
RENOIR II		AWSMT-EAW	ELV	NA	0% - 100%	16% - 100%
RENOIR II		AWSMG-EB	ELV	NA	0% - 100%	16% - 100%
COOPER	SKEY AL	SAL06P	ELV	YES	3% - 100%	0% - 100%
	ASPIRE RF	RF9540-NDW	ELV	YES	27% - 100%	0% - 100%
LEGRAND	PASS & SEYMOUR	H703PTUTC Min 6W	ELV	Auto	18% - 100%	18% - 100%

* Full Dimming Range

** Optimal Performance: Dimming range for ideal synchronized startup conditions

*** The % may vary depending on the number of luminaire used

The use of incandescent dimmers with LED is not recommended by dimmer manufacturers.

For any compatibility problems, consult the dimmer manufacturer.

Note: Contrast Lighting cannot be held responsible of any compatibility problems between dimmers and Contrast Lighting fixtures.

CONTRASTE

ARDITO 3-1/2" & 4"

Performance 2 / 0-10V
Lumileds Luxeon COB 1205
ERP ESS030W-0550-42

CONTRASTE

DIMMING INFORMATIONS

- Dimmers used: 0-10V
- Audible noise: None
- Number of units tested: 1 to 10

Company	Models	Codes	Types	Dimming Performances		
				Programmable	Dimming Range *	Optimal Performance **
LEVITON	ILLUMATECH	IP710-LFZ	0-10V	NA	23% - 100%	35% - 100%
	RENOIR II	AWSWG-7DW	0-10V	NA	23% - 100%	35% - 100%

* Full Dimming Range

** Optimal Performance: Dimming range for ideal synchronized startup conditions

The use of incandescent dimmers with LED is not recommended by dimmer manufacturers.

For any compatibility problems, consult the dimmer manufacturer.

Note: Contrast Lighting cannot be held responsible of any compatibility problems between dimmers and Contrast Lighting fixtures.

CONTRASTE